SIEMENS

Data sheet

6ES7331-7PF01-0AB0



SIMATIC S7-300, Analog input SM 331, isolated, 2/3/4-wire, 8 AI, Resistor, Pt100/200/1000 NI100/120/200/500/1000, CU10, characteristics according to GOST 16 (internal 24) bit, 50ms, 1x 40-pole

Figuresir	nilar
-----------	-------

Supply voltage	
Load voltage L+	
 Rated value (DC) 	24 V
 Reverse polarity protection 	Yes
Input current	
from load voltage L+ (without load), max.	240 mA
from backplane bus 5 V DC, max.	100 mA
Power loss	
Power loss, typ.	4.6 W
Analog inputs	
Number of analog inputs	8
 For resistance measurement 	8
permissible input voltage for voltage input (destruction	75 V; 35 V continuous, 75 V for max. 1 s (mark to space ratio 1:20)
limit), max.	
Input ranges	
Voltage	No
Current	No
Thermocouple	No
 Resistance thermometer 	Yes
Resistance	Yes
Input ranges (rated values), voltages	
• 0 to +10 V	No
• 1 V to 5 V	No
• 1 V to 10 V	No
• -1 V to +1 V	No
• -10 V to +10 V	No
• -2.5 V to +2.5 V	No
• -250 mV to +250 mV	No
• -5 V to +5 V	No
• -50 mV to +50 mV	No
• -500 mV to +500 mV	No
• -80 mV to +80 mV	No
Input ranges (rated values), currents	
• 0 to 20 mA	No
• -10 mA to +10 mA	No
• -20 mA to +20 mA	No
• -3.2 mA to +3.2 mA	No
• 4 mA to 20 mA	No
Input ranges (rated values), thermocouples	
• Type B	No

Turne Q	NI-
• Type C	No
• Туре Е	No
• Туре Ј	No
• Туре К	No
• Type L	No
• Type N	No
• Type R	No
• Type S	No
• Туре Т	No
• Type U	No
Type TXK/TXK(L) to GOST	No
Input ranges (rated values), resistance thermometer	
• Cu 10	Yes
• Ni 100	Yes
• Ni 1000	Yes
• LG-Ni 1000	Yes
• Ni 120	Yes
• Ni 200	Yes
• Ni 500	Yes
• Pt 100	Yes
• Pt 1000	Yes
• Pt 200	Yes
• Pt 500	Yes
Input ranges (rated values), resistors	
• 0 to 150 ohms	Yes
• 0 to 300 ohms	Yes
• 0 to 600 ohms	Yes
Characteristic linearization	
 parameterizable 	Yes
 for resistance thermometer 	Pt100, Pt200, Pt500, Pt1000, Ni100, Ni120, Ni200, Ni500, Ni1000,
	Cu10; (standard/climate)
Cable length	
 shielded, max. 	200 m
 shielded, max. Analog value generation for the inputs 	200 m
	200 m
Analog value generation for the inputs	200 m 16 bit; Two's complement
Analog value generation for the inputs Integration and conversion time/resolution per channel	
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable	16 bit; Two's complement Yes
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max.	16 bit; Two's complement
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for resistance measurement with four-wire connection	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for resistance measurement with four-wire connection • Resistance measurement with four-wire connection • Resistance measurement with four-wire connection • Resistance thermometer, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-)	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for resistance measurement with four-wire connection • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Basic error limit (operational limit at 25 °C)	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes 0.1 % ±1 K
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with four-wire connection • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Basic error limit (operational limit at 25 °C) • Resistance, relative to input range, (+/-)	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes O.1 % ±1 K
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • for resistance measurement with four-wire connection • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Basic error limit (operational limit at 25 °C)	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes 0.1 % ±1 K
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with four-wire connection • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance thermome	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes O.1 % ±1 K
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with four-wire connection • Basic error limit in overall temperature range • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-)	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes 0.1 % ±1 K 0.05 % ±0.5 K
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with four-wire connection • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistanc	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes O.1 % ±1 K
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance thermom	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes 0.1 % ±1 K 0.05 % ±0.5 K Yes; Parameterizable
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection Errors/accuracies Operational error limit in overall temperature range • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resistance thermometer, relative to input range,	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes Yes 0.1 % ±1 K 0.05 % ±0.5 K
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection Errors/accuracies Operational error limit in overall temperature range • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to i	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes 0.1 % ±1 K 0.05 % ±0.5 K Yes; Parameterizable Yes; Parameterizable per group Yes; Parameterizable
Analog value generation for the inputs Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable • Basic conversion time (ms) • Interference voltage suppression for interference frequency f1 in Hz Encoder Connection of signal encoders • for resistance measurement with two-wire connection • for resistance measurement with three-wire connection • for resistance measurement with four-wire connection • Resistance, relative to input range, (+/-) • Resistance, relative to input range, (+/-) • Resistance thermometer, relative to input range, (+/-) • Resist	16 bit; Two's complement Yes up to 4 channels: 10 ms per module, over 5 channels: 190 ms per module, 8 channels: 80 ms 400 / 60 / 50 Hz Yes; without resistance correction Yes Yes Yes 0.1 % ±1 K 0.05 % ±0.5 K

Diagnoses	
 Diagnostic information readable 	Yes
Diagnostics indication LED	
 Group error SF (red) 	Yes
Potential separation	
Potential separation analog inputs	
 between the channels 	Yes
 between the channels, in groups of 	2
 between the channels and backplane bus 	Yes
 between the channels and the power supply of the electronics 	Yes
Isolation	
Isolation tested with	500 V DC
connection method / header	
required front connector	40-pin
Dimensions	
Width	40 mm
Height	125 mm
Depth	120 mm
Weights	
Weight, approx.	272 g
	_

last modified:

1/16/2021 🖸